



## General Description

The TSE-H9000-U is a High Voltage Transformer for insect / bug killers and Ionization application. Because the TSE-H9000-U is a true high voltage Transformer,

It is extremely easy to apply, minimizing design and production costs, and improving time to market.

### Applications

- Insect killers
- Industrial / Home Ionization Products

## Electrical Characteristics / Features

<b>Primary Input</b>	<b>120 Voltages, 60Hz <math>\pm</math> 10%</b>
<b>Secondary Output</b>	<b>9000 Voltages, R.M.S. <math>\pm</math> 15%</b>
<b>Power</b>	<b>50 VA (MAX.)</b>

**The attaching page are the most update drawing for the transformer physical dimension.**

---

**TAT SING ELECTRONICS CO., LTD**

**FLAT 3,3/F., 21-23 SHING WAN ROAD, KINGLET INDUSTRIAL BUILDING,  
SHATIN, N.T., KOWLOON, HONG KONG.**

**TEL: +852-26056607, FAX: +852-26932790, E-Mail: [dennislee@hktatsing.com.hk](mailto:dennislee@hktatsing.com.hk)  
THIS INFORMATION IS BELIEVED TO BE A ACCURATE AND RELIABLE.**

©1999 TAT SING ELECTRONICS CO., LTD.

---