



General Description

The TSE-H4000-E is a High Voltage Transformer for insect / bug killers and Ionization application. Because the TSE-H4000-E is a true high voltage Transformer,

It is extremely easy to apply, minimizing design and production costs, and improving time to market.

Applications

- Insect killers
- Industrial / Home Ionization Products

Electrical Characteristics / Features

Primary Input	240 Voltages, 50Hz $\pm 10\%$
Secondary Output	4000 Voltages, R.M.S. $\pm 10\%$
Power	50 VA (MAX)

The attaching page are the most update drawing for the transformer physical dimension.

TAT SING ELECTRONICS CO., LTD

**FLAT 3,3/F., 21-23 SHING WAN ROAD, KINGLET INDUSTRIAL BUILDING,
SHATIN, N.T., KOWLOON, HONG KONG.**

TEL: +852-26056607, FAX: +852-26932790, E-Mail: dennislee@tatsingelectronics.com.hk

THIS INFORMATION IS BELIEVED TO BE A ACCURATE AND RELIABLE.

©1999 TAT SING ELECTRONICS CO., LTD.
